

ROP-400/EU

ADDRESSABLE MANUAL CALL POINT

The **ROP-400** call point is used to manually trigger an alarm when a fire is discovered. It is designed to operate in the detection line of the **ACSP-402** addressable fire alarm control panel.

- resettable plastic pane
- **ROP-KEY-U** key (sold in set) to enable:
 - testing
 - resetting

LED indicator

double-sided short-circuit isolator

power supply from the detection line

optional mounting box – **ROP-BT / ROP-BS**

optional protective cover to prevent unintentional activation – **ROP-FLAP**

TECHNICAL DATA

Operating temperature range	-10°C...+55°C
Weight	86 g
Maximum humidity	95%
Dimensions	87 x 87 x 40 mm
Current draw when detecting	170 µA
Current draw when emitting an alarm	450 µA

