

# ManualCallPoint (White) Jeweller

Wireless resettable button featuring programmable scenarios. White-colored version

<b>Compatibility</b>	<b>Control panels</b> Hub Plus Hub 2 (2G) Hub 2 (4G) Hub 2 Plus Hub Hybrid (2G) Hub Hybrid (4G)  <b>Range extenders</b> ReX ReX 2
<b>Communication</b>	<b>Jeweller communication technology</b>  Proprietary wireless communication technology to transmit commands, alarms, and events.  Key features: <ul style="list-style-type: none"><li>• Two-way communication.</li><li>• Advanced anti-sabotage.</li><li>• Block encryption featuring a dynamic key.</li><li>• Instant notifications.</li><li>• Remote configuration in the Ajax apps.</li></ul> <b>Frequency bands</b> 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the region of sale.  <b>Maximum effective radiated power (ERP)</b> up to 25 mW Automatic power control to reduce power consumption and noise interference.  <b>Radio signal modulation</b> GFSK  <b>Radio signal range</b> up to 1,700 m up to 5,500 ft Between button and hub (or range extender) in an open space.  <b>Encrypted communication</b> All stored and transmitted data are protected by block encryption featuring a dynamic key.

	<p><b>Frequency hopping</b> Radio communication uses frequency hopping to prevent interception and jamming.</p>
<p><b>Key features</b></p>	<p><b>Resettable frangible element</b> activates the button When the central part (frangible element) is pressed, the button depresses inward, triggering an alarm or initiating a scenario. Two yellow stripes appear at the top and bottom, indicating the device's state.</p> <p><b>Operating modes</b> fire alarm scenario trigger With appropriate settings, it activates an alarm or controls Ajax automation devices.</p> <p><b>LED status indication</b> fire alarm malfunctions The LED indicator on the device enclosure lights up when a fire alarm is triggered or malfunctions are detected.</p> <p><b>Interconnected fire detectors alarms</b> by pressing the button By pressing the frangible element, fire detectors in the system trigger the built-in sirens.</p> <p><b>Critical alerts</b> The system can activate intrusion sirens and send audible alarm notifications to users, even if the sound is muted, the <b>Do Not Disturb</b> mode is on, or headphones are connected.</p> <p><b>Protection against accidental presses</b> Lift the transparent lid to access the frangible element. The lid protects against false button presses.</p> <p><b>CMS alarm transferring</b> can be disabled for the Blue version only</p>
<p><b>The ManualCallPoint button is available in several versions.</b></p>	
<p><b>Special tool (key)</b></p>	<p><b>Button reset</b> after pressing To reset the button, insert the special tool into the corresponding hole.</p> <p><b>Hole in the enclosure</b> to hang on a ring from a keychain The person responsible for fire safety can carry the special tool on their keychain.</p> <p><b>Convenient dismantling</b></p>

	The special tool opens the lock to dismantle the device from SmartBracket mounting panel.
<b>Recomendations</b>	It is recommended to install the button in easily accessible places at a height of 1.4 m.  The device is designed for indoor installation only.
<b>Sabotage protection</b>	<b>Tamper alarm</b> Notifies on attempts to detach the button from the surface or remove it from the mounting panel.  <b>Protection against spoofing</b> device authentication  <b>Communication loss detection</b> after 36 s The detection time depends on the Jeweller or Jeweller/Fibra settings.
<b>Power supply</b>	<b>Batteries</b> 2 × CR123A Pre-installed. With typical use (one press lasting 1 minute per week), the batteries can last up to 7 years.
<b>Enclosure</b>	<b>Dimensions</b> 102 × 104 × 39 mm 4.02" × 4.09" × 1.53"  <b>Weight</b> 214 g 7.55 oz  <b>Operating temperature range</b> from 0 °C to +50 °C from 32 °F to 122 °F  <b>Operating humidity</b> up to 80%
<b>Complete set</b>	ManualCallPoint (White) Jeweller SmartBracket mounting panel Special tool (key) 2 × CR123A battery (pre-installed) Installation kit Quick start guide
<b>Warranty</b>	24 months